

CCIE Collaboration (<http://labs.ine.com/workbook/toc/ccie-collaboration>) » Cisco IOS UC Applications & Features

## CME Fast Dials/Speed Dials & Local Directory

« CME SIP Phone Security Administration (</workbook/view/ccie-collaboration/task/cme-sip-phone-security-administration-MzA3MA%3D%3D>) | Cisco Unity Express Initialization (</workbook/view/ccie-collaboration/task/cisco-unity-express-initialization-MzA3Mg%3D%3D>) »

Last updated: November 10, 2017

### Tasks

- Site C Phone 1 should see Site C Phone 2 in its Personal Speed Dial and should be able to dial.
- Site C Phone 1 should be able to speed dial Emergency number 999 using key 1.
- All Site C phones should be able to search and dial HQ Phones & Site B Phones using their Local Directory.

### Configuration: [Click to collapse](#)

#### On R3 Gateway

```
ephone 1
  fastdial 1 4002 name Site C Phone 2
  speed-dial 1 999 label Emergency
!
Telephony-service
  directory entry 1 2001 name HQ Phone 1
  directory entry 2 2002 name HQ Phone 2
  directory entry 3 3001 name SiteB Phone 1
!
ip http server (Else you will see "Host Not Found" when you press Directories Button)
```

« CME SIP Phone Security Administration (</workbook/view/ccie-collaboration/task/cme-sip-phone-security-administration-MzA3MA%3D%3D>) | Cisco Unity Express Initialization (</workbook/view/ccie-collaboration/task/cisco-unity-express-initialization-MzA3Mg%3D%3D>) »